



LUMOS DIALBRIGHT 1500

10001879

INSTRUCTIONS



IMPORTANT

Carefully read all instructions before use and save for future reference.

CHARGING

Lumos DialBright 1500 contains a 3.7V lithium-ion battery and comes with a USB charging cable.

Step 1. Open the dust cover at the top of the light.

Step 2. Plug the charging cable into the USB-C outlet.

Step 3. Plug the USB cord into any USB outlet on a computer, wall adapter (not included), etc.

NOTE: Charging while using a USB wall adapter will be faster than a computer USB port.

Step 4. While charging, the digital display screen will show the charging status.

Step 5. Once it reaches 100%, the light is fully charged. Remove the USB cord and store.

Note: Always use the supplied cable for charging. Ensure that the light is fully charged every three months to protect the life of the battery.

OPERATION

Step 1. Press and hold the power button for approximately 3 seconds to turn on the light.

Step 2. Rotate the dials on the back of the light to select the required lumens (120L / 300L / 750L / 1500L) and colour temperature (2700K / 3500K / 4500K / 6500K).

Step 3. Press the power button a second time for solid red.

Step 4. Press the power button a third time for flashing red.

Step 5. Press the power button a fourth time for strobe red.

Step 6. Press the power button a fifth time to return to the white/warm light.

Step 7. Press and hold the power button at any time to turn off the light.

CHARGING SMALL DEVICES

Lumos DialBright 1500 contains a USB-C output port which allows small devices to be charged (mobile phone, tablets, etc.).

Step 1. Open the dust cover at the top of the light.

Step 2. Plug the USB cord that comes with the small device that is being charged into the output port.

Step 3. Charge the device as required.

MOUNTING OPTIONS

Lumos DialBright 1500 has four different mounting options.

Table Top

Step 1. Stand the light on a flat surface.

Step 2. Rotate the light on the stand for directional lighting options.

Magnet

Heavy duty magnets are located on the base of the stand.

Step 1. Attach the light to a metal surface.

Step 2. Rotate the light on the stand for directional lighting options.

Hook

A hook is located in the stand.

Step 1. Open the lever style bracket and hook onto a bar of choice.

Step 2. Rotate the light on the stand for directional lighting options.

Tripod

A tripod screw point is located in the stand.

Step 1. Screw a tripod to the light (tripod not included).

Step 2. Rotate the light on the stand for directional lighting options.

NOTE: Ensure that the light is securely attached to avoid damage or injury.



TABLE TOP



MAGNET



HOOK



TRIPOD

WARNING

1. Ensure that the unit is charged every three months to protect the life of the battery.
2. Store the unit away from water, heat sources and metal objects.
3. Store the unit in a cool, dry place to prolong the battery life.
4. Do not impact, puncture, or drop the light.
5. Do not leave the unit unattended while charging/using the powerbank feature of the light.
6. Do not look directly into the light.

SPECIFICATIONS

Dimensions	11.4L x 5.7W x 11.7H cm
Weight	430g
Light modes	Main, red, red flashing, red strobe
Lumens	120 (low) / 300 (medium) / 750 (high) / 1500 (max)
Colour temperature	2700K (low) / 3500K (medium) / 4500K (high) / 6500K (max)
Beam Distance	5m (low) / 9m (medium) / 17m (high) / 28m (max)
Runtime (approx)	64hrs (low) / 24hrs (medium) / 14hrs (high) / 7.5hrs (max)
Water Resistance	IP54
Battery	3.7V 2 x 4800mAh lithium rechargeable
Charge time	6.5hrs



WARRANTY - For details see www.oztrail.com.au/warranty
OZtrail® is a registered trademark of
Adventure Trading Australia Pty Ltd

Designed by:
Adventure Trading Australia Pty Ltd
71 Charles Ulm Place, Eagle Farm,
QLD 4009, AUSTRALIA
Made in China

